

## RMX-6000B VIDEO RECEIVER

This is a special audio/video receiver for 5.8 GHz with continues frequency range from 5,66 MHz - 6,00 GHz. Fully synthesized this receiver has an SMA connector for different type of antennas. The frequency step is 250 kHz with built-in fast scanning function.



### Features:

- ◆ 5.8 GHz Wideband
- ◆ Fully tunable
- ◆ SMA antenna connector
- ◆ 12 V battery operated
- ◆ 1 V video output
- ◆ Excellent picture quality
- ◆ High sensitivity

Technical Specifications	VRX-24S
Digitally Controlled	Yes
Polarity Protected	Yes
Battery power:	12 V
Sensitivity:	-86 dBm
Antenna Connector:	SMA
Current Consumption:	395 mA
Audio output	300 mV
Video Output	1V
Temperature Range:	-20 +70 °C
Dimensions:	4" X 6.5" X 2"
Demodulation	WFM
Number of Channels	Full range tunable



[www.rf-video.com](http://www.rf-video.com)

Email to: [info@rf-video.com](mailto:info@rf-video.com)  
 Copyright. © 2000-2012