
HDMR-54

Audio/Video Receiver 5.4 GHz

This is a special audio/video receiver with an LCD screen 4.3" for 5.4 GHz Fully synthesized this receiver has an SMA connector for different type of antennas for 5.4 GHz. This receiver has 8 preprogrammed channels. This receiver has built-in low noise preamplifier 12 dB gain for 5.4-5.9 GHz band.

Dimensions: 4.45 " X 3.6 " X 1.2 " .



| Technical Specifications | |
|--------------------------|-----------------------|
| BATTERY POWERED | 12 V |
| CURRENT CONSUMPTION | 455 mA |
| DEMODULATION | WFM |
| SENSITIVITY | -86 dBm |
| ANTENNA CONNECTOR | SMA |
| FREQUENCY: | 5.4 GHz |
| VIDEO OUTPUT | 1V |
| AUDIO OUTPUT | 300 mV |
| POLARITY PROTECTED | YES |
| PLL (PHASE LOOKED LOOP) | YES |
| TEMPERATURE RANGE: | -20+70°C |
| NUMBER OF CHANNELS | 8 INTERNALLY SELECTED |
| DIMENSIONS | 4.45" X 3.6" X 1.2" |
| VIEWING SCREEN: | 4.3" |