
R-58

Audio/Video Receiver

5.4 GHz

This small receiver is definitely the best 5.4 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.4 GHz. This receiver has 8 channels in 5.8 GHz band.



| Technical Specifications | |
|---------------------------|--------------------|
| Operating Frequencies: | 5400 MHz BAND |
| Channel: | Channels from 1-8 |
| DC Voltage: | 9 V – 12 V |
| Sensitivity: | -86 dBm |
| Minimum required voltage: | 10 V |
| Battery power: | 7.4 V |
| Video distortion: | 3% |
| Maximum range: | N/A |
| Video Format: | PAL, NTSC |
| Current Consumption: | 350 mA / 7.4 V |
| Antenna: | N/A |
| Antenna Connector: | SMA |
| Impedance: | 50 ohms |
| Audio outputs: | 300 mV |
| Video/Audio Connectors: | RCA F |
| Video Impedance: | 75 ohms |
| Video level: | 1 V |
| Temperature Range: | -10 +65 °C |
| Dimensions: | 4.8" X 2.8" X 0.9" |
| Weight: | 100 grams |
| Demodulation: | WFM |